

Add:

#### SHENZHEN Rose Lighting Technology CO., LTD

### 深圳市薔薇照明科技有限公司

No.53 Yuexing Rd, Guanlan Street ,Longhua District,Shenzhen, China,zipcode:518110

# RL-3812-ICRGB

### **Specifications**

Picture	Dimension	Parameters	
Car		Input voltage	DC 24V
		Lamp power	2.88W
	Outline Dimension:(Unit:mm)  Signal  OC 24V- DAT OND	Chip	UCS 2903
		LED chip	SMD 3535
		LEDs number	12
		Color	RGB programmable
		IP rating	IP65
		Beam angle	≥140°
		Lifespan	≥50000h

#### **Features**

- 1. This product is made up of PCB. Milky/Transparent plastic cover and base, a couple of 3-pins male and female connectors. As well as a series of gluing process to ensure good water and UV resistance.
- 2. It is a RGB programmable product, can achieve many different light effects by using a LED controller such as K-1000c.
- 3. The features of this product are high brightness, low power dissipation, long lifespan, low voltage decline and excellent thermal management and lumen maintenance.
- Customized requests are available, for example: logo, waterproof connectors, transparent or milky cover, and length of cables.
- 5. This product has CE and RoHS certifications.

### **Applications**



1. Amusement Park Rides Light

Ferris wheel, Carousels, Pirate ship, Pendulum, Bumper car, Tower and so on.

2. Advertisement Outdoor Signboard Backlight

Logo, Signage, Channel letter, Signs, Exposed luminous characters, Billboard and so on.

Tel: 0755-23763467 Email: info@rose-lighting.com Web: https://www.rose-lighting.com/



#### SHENZHEN Rose Lighting Technology CO., LTD

### 深圳市薔薇照明科技有限公司

Add: No.53 Yuexing Rd, Guanlan Street ,Longhua District,Shenzhen, China,zipcode:518110

3. Stage Decoration Light

KTV, Disco, Bar, Night club and other stage light.


4. Commercial Light

Hotel, Shopping mall, Theater, Square and so on.

5. Kids Rides Decoration


Castles, Robot, Mini carousels, Car, Mini train etc.

## Packing & Weight



Weight/100pcs	Pieces/bag	Pieces/carton	G.W/carton	Carton size
1.4kg	100pcs	480pcs	16kg	46.5cm*46cm*28cm

## **Connection**



#### **Notes:**

- 1. Male connector (with pins) is signal input port, female connector (without pins) is signal output port.
- 2. We suggest that every 20pcs lights connect to the power supply in parallel to avoid voltage decline.
- 3. One controller can only support up to 2000 pixels, more than 2000 pixels, you need to cascade with multiple controllers.

Tel: 0755-23763467 Email: info@rose-lighting.com Web: https://www.rose-lighting.com/