


HOW TO ADD UNIVERSE BY MANUAL ON BC-216


Now show you how to add the universe by manual, one universe can control 170 pixels . Press F4, then Pop up a window, as follow



Click Art-Net → click New... key



Then click OK. ,Then pop up new window as follow,



Setup the information on newly-built window.

Art-Net Device Configuration

Manufacturer : unknown

Product : developer Firmware: v3.1

OEM Code : 0x00FF

Est: 0x4941 - inoage GmbH

Short Name : **ArtNet 0095** long name of this artnet device (max 63 chars)

Long Name : **ArtNet device nr 0095**

Port Count : **1**

State : Port 1: Disabled

Universe

Universe Port OUT : **1 (0x00)** →

Port IN :

UUID : 580e1d6b-e352-4d7f-a3e8-86c9ee24d344

Style Code : node

Port : 6454 0x1936

Send Direct : ☐ Send Data Only To Address 192.168.0.95

IP : **192 . 168 . 0 . 95** **MAC To IP**

Send Broadcast : ☐ Send Data To "Directed Broadcast Address" 192.168.0.255

Network : **192.168.0.137 255.255.255.0 00:30:67:EE:CC:B9 100 MBit/s**

OK **Apply** **Cancel**

here amend the universe No. which need to be setup

Click and amend to specified IP

For example, the added universe port out No. is 57, and specified IP is 192.168.0.153, so setup information is as follow,

Art-Net Device Configuration

Manufacturer : unknown

Product : developer Firmware: v3.1

OEM Code : 0x00FF

Est: 0x4941 - inoage GmbH

Short Name : **ArtNet 0095** Manual ID : 95

Long Name : **ArtNet device nr 0095**

Port Count : **1**

State : Port 1: Disabled

Universe

Universe Port OUT : **57 (0x38)**

Port IN :

UUID : 580e1d6b-e352-4d7f-a3e8-86c9ee24d344

Style Code : node

Port : 6454 0x1936

Send Direct : ☒ Send Data Only To Address 192.168.0.95

IP : **192 . 168 . 0 . 153** **MAC To IP**


Send Broadcast : ☐ Send Data To "Directed Broadcast Address" 192.168.0.255

Network : **192.168.0.137 255.255.255.0 00:30:67:EE:CC:B9 100 MBit/s**

OK **Apply** **Cancel**

after set the information, click OK.

Switch to **DMX Devices** interface,



For example, the added universe port out No. is 57,

Click and select, then input 57 on **universe** column on the right window, and click “Apply” is OK . as follow:

